

Split core current transformes

Sensor type 2 - Standard size current clamp	
Cable window	24 mm
Dimensions (LxHxW)	44,5 x 65 x 33,5 mm
Selectable ranges by Joystick	20 - 40 - 80 - 200 A
Cable length	2m
Sensor type 3 - Miniature size current clamp	
Cable window	16 mm
Dimensions (LxHxW)	30 x 43,5 x 30 mm
Selectable ranges by Joystick	10 - 20 - 40 - 100 A
Cable length	2m
Sensor type 4 - Mini-transformer (CT) with output voltage	
Cable window	6mm
Dimensions (LxHxW)	16 x 32 x 26,4 mm
Selectable ranges by Joystick	1 - 2 - 5 - 10 A
Cable length	2m

Sensors extension	
Compatible with all sensors	
Cable length	4m

